

```

mkfifo          mkfs.cramfs      mkfs.minix      mkinitramfs     mkntfs
mkfontdir       mkfs.ext2       mkfs.msdos     mkisofs         mksquashfs
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$ mkdir -p ~/Document/Depot_Patient
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$ whoami
adminlocal
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$ ls
Bureau Document Documents Images Modèles Musique Public Téléchargements Vidéos
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$ nano /home/adminlocal/isolement_chd.sh
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$ lsblk
NAME                                MAJ:MIN RM  SIZE RO TYPE  MOUNTPOINTS
sda                                  8:0      0 119,2G  0 disk
├─sda1                              8:1      0    1M  0 part
├─sda2                              8:2      0  513M  0 part  /boot/efi
├─sda3                              8:3      0   1,7G  0 part  /boot
├─sda4                              8:4      0 117,1G  0 part
├─sda4_crypt                       252:0    0 117,1G  0 crypt
├─vgzorin-root                     252:1    0 115,1G  0 lvm  /
└─vgzorin-swap_1                   252:2    0   1,9G  0 lvm  [SWAP]
sdb                                  8:16     1  29,3G  0 disk
├─sdb1                              8:17     1  29,3G  0 part
└─bitlk-4bf92597-d209-4ef0-be0e-89fbd1342da1 252:3    0  29,3G  0 crypt /media/adminlocal/USB_CHD
sr0                                  11:0     1 1024M  0 rom
adminlocal@adminlocal-HP-ProDesk-400-63-SFF:~$

```

Poste Zorin – Règle de filtrage :

- Etape 1 : Verifier l'ID et le numero de serie si necessaire → lsubst (id) ; udevadm info --attribute-walk --name=sdb1 | grep "serial "
- Etape 2 : créer un fichier → sudo nano /etc/udev/rules.d/99-block-usb.rules
- Contenu :

```
SUBSYSTEMS=="usb", ATTRS{idVendor}=="346d", ATTRS{idProduct}=="5678", ATTRS{serial}=="6593141085259147444", ATTR{authorized}="1", GOTO="usb_end"
```

```
SUBSYSTEMS=="usb", ATTR{bInterfaceClass}=="03", ATTR{authorized}="1", GOTO="usb_end"
```

```
SUBSYSTEMS=="usb", ATTR{bInterfaceClass}=="08", ATTR{authorized}="0"
```

```
LABEL="usb_end"
```